

Technical Data Sheet

Plenum MiniMax® CCTV Coaxial Cable



2833 West Chestnut Street
 Washington, PA 15301
 Toll Free: (800) 245-4964
 Fax: (724) 222-6420
 www.westpenn-wpw.com

PART NUMBER:	825
DESCRIPTION:	MiniMax – 1 Conductor 25AWG Solid, 95% Bare copper braid and an overall PVC Jacket.
NEC RATING:	CMP/CL2P
APPROVALS:	(UL) C(UL) Listed or c(ETL)us Listed
APPLICATION:	Indoor for: Security Cable – CCTV - Plenum

Construction Parameters:

Conductor	25 AWG Bare Copper
Stranding	Solid
Insulation Material	Foam FEP - Teflon
Insulation Thickness	0.078" Nom.
Number of Conductors	1 Center Conductor
Shield	95% Bare Copper Braid
Jacket Material	Flex Plenum
Overall Cable Diameter	0.146" Nom.
Approximate Cable Weight	10 Lbs/1M' Nom.
Flame Rating	UL NFPA 62

Electrical & Environmental Properties:

		<u>Mhz</u>	<u>db/100ft</u>
Temperature Rating	-20deg C to 60deg C	1	.5
Max. Capacitance Between Conductors @ 1 KHz	16.2 pf/ft Nom.	10	1.80
Velocity of Propagation	82% Nom.	50	3.12
Impedance	75 ohms Nom.	100	4.40
DC Resistance per Conductor @ 20deg C	30 Ohms/1M' Nom.	400	9.66
Jacket Color	Black, Red, Green, Blue, White, Yellow	700	12.61
RoHS Compliant	Yes	1000	16.18

Mechanical Properties:

Max. Recommended Pull Tension	16 lbs.
Min. Bend Radius (Install)	1.5"

Connectors and Accessories

75 ohm BNC Crimp	CN-BM74-18	Crimp Tool: TL-105	Strip Tool: TL-825
75 ohm BNC Compression	CN-BNCP-825	Comp. Tool: TL-SNSA	Strip Tool: TL-CSST
1 Pc. Compression BNC 75 ohm	CN-FS15BNC	Comp. Tool: TL-SNSA	Strip Tool: TL-CSST
Compression RCA	CN-RCP-825	Comp. Tool: TL-SNSA	Strip Tool: TL-CSST
Female BNC Type	CN-BF74-18	Crimp Tool: TL-105	Strip Tool: TL-825

Specification Issue Date: 7/06

This document is the property of West Penn Wire.
 The information contained herein is considered
 Proprietary and not to be reproduced by any means
 Without written consent of West Penn Wire

Standard Lengths are 1000ft.
 The Jacket is sequentially footmarked.
 The information presented here is, to the best of our
 knowledge, is true and accurate. However, since
 conditions of use are beyond our control, all
 recommendations or suggestions are presented
 without guarantee or responsibility on our part. We
 disclaim all liability in connection with the use of
 information contained herein or otherwise.

